



Uni-directional 15V High Capacitance ESD Protector

Description

The PESDHC2FD15VU ESD protector is designed to replace multilayer varistors (MLVs) in portable applications such as cell phones, notebook computers, and PDA's. They feature large cross-sectional area junctions for conducting high transient currents, offer desirable electrical characteristics for board level protection, such as fast response time, lower operating voltage, lower clamping voltage and no device degradation when compared to MLVs. The PESDHC2FD15VU protects sensitive semiconductor components from damage or upset due to electrostatic discharge (ESD) and other voltage induced transient events. The PESDHC2FD15VU is available in a DFN1006-2L package with working voltages of 15 volt. It gives designer the flexibility to protect one unidirectional line in applications where arrays are not practical. Additionally, it may be "sprinkled" around the board in applications where board space is at a premium.



DFN1006-2L(Bottom View)



Feature

- \gt 450W peak pulse power per line (t_p = 8/20µs)
- ➤ DFN1006-2L package
- > Response time is typically < 1 ns
- Unidirectional configurations
- Low clamping voltage
- ➤ RoHS compliant
- ➤ Transient protection for data lines to IEC 61000-4-2(ESD) ±30kV(air), ± 30kV(contact); IEC 61000-4-5 (Lightning) 18A (8/20us)



Marking (Top View)

Applications

- Cell phone handsets and accessories
- Personal digital assistants (PDA's)
- Notebooks, desktops, and servers
- Portable instrumentation
- > Cordless phones
- Digital cameras
- > Peripherals


Mechanical Characteristics

- Mounting position: Any
- Qualified max reflow temperature:260°C
- > Device meets MSL 1 requirements
- DFN1006-2L without plating

ESD Protector

Electronics Parameter

Symbol	Parameter			
V_{RWM}	Peak Reverse Working Voltage			
I _R	Reverse Leakage Current @ V _{RWM}			
V_{BR}	Breakdown Voltage @ I _T			
I _T	Test Current			
I _{PP}	Maximum Reverse Peak Pulse Current			
V _C	Clamping Voltage @ I _{PP}			
P _{PP}	Peak Pulse Power			
C _J	Junction Capacitance			
I _F	Forward Current			
V _F	Forward Voltage @ I _F			



Electrical characteristics per line@25°C (unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Peak Reverse Working Voltage	V_{RWM}	-	-	-	15	V
Breakdown Voltage	V_{BR}	I _t = 1mA	16	-	18.5	V
Reverse Leakage Current	I _R	V _{RWM} = 15V	-	-	1	μA
Clamping Voltage ¹⁾	V _C	TLP = 16A, $t_p = 100 \text{ns}$	-	20	-	V
Dynamic resistance ¹⁾	R_{DYN}	-	-	0.15	-	Ω
Clamping Voltage ²⁾	V _c	$I_{PP} = 1A, t_P = 8/20 \mu s$	-	18.5	20	V
		$I_{PP} = 18A, t_{P} = 8/20 \mu s$	-	25	28	V
Junction Capacitance	С	$V_R = 0V, f = 1MHz$	-	100	130	pF

Notes:

Absolute maximum rating@25°C

Rating	Symbol	Value	Units
Peak Pulse Power (t _P = 8/20µs)	P _{PP}	450	W
Peak Pulse Current (t _P = 8/20μs)	I _{PP}	18	А
Lead Soldering Temperature	T _L	260 (10 sec)	°C
Junction and Storage Temperature Range	$T_{J_{I}}T_{STG}$	-55~+150	°C
ESD Protection-Contact Discharge	V _{ESD}	±30	kV
ESD Protection-Air Discharge	V _{ESD}	±30	kV

^{1.}TLP parameter: Z_0 =50 Ω , t_p =100ns, t_r =2ns, averaging window from 60ns to 80ns. R_{DYN} is calculated from 4A to 16A. 2.Non-repetitive current pulse, according to IEC61000-4-5.

Typical Characteristics




Fig 5. Non Repetitive Peak Pulse Power vs. Pulse time

Fig 6. TLP Measurement

ESD Protector

PESDHC2FD15VU




Fig 7. Clamping Voltage at IEC61000-4-2 +8kV Pulse Waveform





Fig 8. Clamping Voltage at IEC61000-4-2 -8kV Pulse Waveform

Solder Reflow Recommendation



Remark: Pb free for 260°C; Pb for 245°C.

PCB Design


For TVS diodes a low-ohmic and low-inductive path to chassis earth is absolutely mandatory in order to achieve good ESD protection. Novices in the area of ESD protection should take following suggestions to heart:

- > Do not use stubs, but place the cathode of the TVS diode directly on the signal trace.
- > Do not make false economies and save copper for the ground connection.
- > Place via holes to ground as close as possible to the anode of the TVS diode.
- Use as many via holes as possible for the ground connection.
- ➤ Keep the length of via holes in mind! The longer the more inductance they will have.

Ordering information


Device	Package	Reel	Shipping
PESDHC2FD15VU DFN1006-2L (Pb-Free)		7"	10000 / Tape & Reel


Load with information




Unit:mm


Product dimension (DFN1006-2L)







Dim	Millimeters		Inches		
	Min	Max	Min	Max	
Α	0.340	0.498	0.013	0.020	
В	0.000	0.050	0.000	0.002	
С	0.950	1.080	0.037	0.043	
D	0.550	0.680	0.022	0.027	
Е	0.400	0.600	0.016	0.024	
F	0.200	0.300	0.008	0.012	
Н	0.400 Typ.		0.015 Typ.		



Suggested PCB Layout

IMPORTANT NOTICE

and Prisemi are registered trademarks of Prisemi Electronics Co., Ltd (Prisemi), Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: http://www.prisemi.com
For additional information, please contact your local Sales Representative.

©Copyright 2009, Prisemi Electronics

Prisemi is a registered trademark of Prisemi Electronics.

All rights are reserved.