


Description

The enhancement mode MOS is extremely high density cell and low on-resistance.

MOSFET Product Summary		
V _{DS} (V)	R _{DS(on)} (mΩ)	I _D (A)
-30	43 @ V _{GS} =-10V	-4.2
	53 @ V _{GS} =-4.5V	


Electrical characteristics per line@25°C (unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Units
OFF CHARACTERISTICS						
Drain-Source Breakdown Voltage	BV _{DSS}	I _D = -250μA, V _{GS} = 0V	-30	-	-	V
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} = -24V, V _{GS} = 0V	-	-	-1	μA
Gate-Body Leakage Current	I _{GSS}	V _{DS} = 0V, V _{GS} = ±12V	-	-	±100	nA
Gate Threshold Voltage	V _{GS(th)}	V _{DS} = V _{GS} , I _D = -250μA	-0.45		-1.3	V
Static Drain-Source On-Resistance	R _{DS(ON)}	V _{GS} = -10V, I _D = -4.2A	-	43	55	mΩ
		V _{GS} = -4.5V, I _D = -4A	-	53	65	mΩ
		V _{GS} = -2.5V, I _D = -2A		79	90	mΩ
Forward Trans conductance	g _{FS}	V _{GS} = -5V, I _D = -5A, T _A = 125°C	7	11		S
DYNAMIC PARAMETERS						
Input Capacitance	C _{ISS}	V _{GS} = 0V, V _{DS} = -15V, f = 1MHz	-	950		pF
Output Capacitance	C _{DSS}		-	110		pF
Reverse Transfer Capacitance	C _{RSS}		-	75		pF
SWITCHING PARAMETERS						
Turn-On Delay Time	t _{d(on)}	V _{DD} = -15V, V _{GS} = -10V, R _L = 3.6Ω, R _G = 6Ω	-		20	ns
Turn-Off Delay Time	t _{d(off)}		-		35	ns

Absolute maximum rating@25°C

Parameter	Symbol	Value	Units
Thermal Resistance, Junction-to-Ambient	R _{θJA}	104	°C/W

Absolute maximum rating@25°C

Rating		Symbol	Value	Units
Drain-Source Voltage		V_{DS}	-30	V
Gate-Source Voltage		V_{GS}	± 12	V
Drain Current	Continuous	I_D	-4.2	A
	Pulsed	I_D	-30	A
Maximum Power Dissipation		P_D	1.2	W
Operating Junction and Storage Temperature Range		T_J, T_{STG}	-55 To 150	°C

Typical Characteristics




Fig 1. Power Dissipation




Fig 2. Drain Current




Fig 3. Output Characteristics




Fig 4. Drain-Source On-Resistance




Fig 5. Transfer Characteristics




Fig 6. Transfer Characteristics




Fig. 7 R_{dson} vs V_{GS}




Fig.8 Capacitance vs V_{DS}




Fig. 9 Gate Charge




Fig.10 Source- Drain Diode Forward




Fig. 11 Safe Operation Area






Fig.12 Normalized Maximum Transient Thermal Impedance

Solder Reflow Recommendation




Remark: Pb free for 260°C; Pb for 245°C.

Product dimension(SOT-23)



Dim	Millimeters		Inches	
	MIN	MAX	MIN	MAX
A	2.80	3.04	0.1102	0.1197
B	1.20	1.40	0.0472	0.0551
C	2.10	2.50	0.0830	0.0984
D	0.89	1.02	0.0350	0.0401
E	0.45	0.60	0.0177	0.0236
F	1.78	2.04	0.0701	0.0807
G	0.085	0.177	0.0034	0.0070
H	0.45	0.60	0.0180	0.0236
J	0.37	0.50	0.0150	0.0200
K	0.89	1.11	0.0350	0.0440
L	0.013	0.100	0.0005	0.0040
θ	0°	10°	0°	10°


Marking information



Ordering information


Device	Package	Reel	Shipping
PPMT30V4	SOT-23	7"	3000 / Tape & Reel

Load with information



Unit:mm


IMPORTANT NOTICE

 and **Prisemi**[®] are registered trademarks of **Prisemi Electronics Co., Ltd** (Prisemi). Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: <http://www.prisemi.com>

For additional information, please contact your local Sales Representative.

©Copyright 2009, Prisemi Electronics

 **Prisemi**[®] is a registered trademark of Prisemi Electronics.

All rights are reserved.